

Martin PFENNIGBAUER, Andreas ULLRICH

RIEGL Laser Measurement Systems GmbH / Austria

www.riegl.com




- VMX-250 technology echo digitization / online waveform processing ranging / precision performance
 - point density / scan pattern considerations multi-target capability
- VMX-250 results


www.riegl.com


RIEGL Laser Measurement Systems









































RIEGL calibrates the systems amplitude reading such that the amplitude for each measurement A_{dB} is given in dB over the detection threshold for the entire dynamic range of the instrument:

$$A_{dB} = 10 \cdot \log \left(\frac{P_{coho}}{P_{DL}} \right)$$

where P_{echo} is the optical input power for the corresponding measurement and P_{DL} is the minimum detectable input power.

Thus, signal strength ratios in dB between different targets can be obtained simply by calculating the difference between the corresponding amplitude values:

$$10 \cdot \log \left(\frac{P_{echo,1}}{P_{echo,2}} \right) = A_{db,1} - A_{db,2}$$

Terrestrial Scanning Mobile Scanning Airborne Scanning

Industrial Scanning

www.riegl.com

Calibrated amplitude and reflectance reading



the "relative reflectance" is proportional to the logarithmic ratio of the target's reflectance over a perfectly white diffuse reflector

$$\rho_{rel} = A_{dB} - A_{dB,Ref}(R)$$

Reflectance is the ratio of the optical power reflected in any direction Prefl to the total impinging optical power Ptot, which may also interpreted as the relative portion of power not absorbed by the target:

 $\rho = \frac{P_{refl}}{P_{tot}} = 1 - \frac{P_{obs}}{P_{tot}}$

The relative reflectance is the ratio of the absolute reflectance of a target to the reflectance of the target the instrument was calibrated with, i.e. a white reflectance standard with 98%

Thus, white diffuse targets would have assigned about 0dB, black paper would give about - $10dB - \underline{indifferent}$ to the object's actual distance from the scanner.

www.riegl.com

Calibrated amplitude and reflectance reading

